SI-MHCS Heat Control System

For the control of voltage applied to inductive and resistive heating elements







Rated operational current: 70 to 500 A Main voltage: Up to 13.8 kV

The **SI-MHCS** is a heavy duty, fully digital, zero-crossing, 3-phase control power unit for all types of resistive loads, intended for the control of any Medium Voltage heating applications. Using Medium Voltage drastically reduces the amount of cable required, the size of the heating elements and of the electrical equipment cabinets in addition to savings with other unnecesary costly step-down transformers.

Advanced Features

- Zero crossing & phase control (field programmable)
- » Comprehensive protection package
- » Communication: Modbus
- » Line and Inside delta connection
- Synchronized mode (up to 10 units)

Models | Up to 13.8kV, 500A

Mains Voltage (kV)	Rated Current (A)	Heater kW @6.6kV	Unit Dimensions (mm)		
			Н	W	D
4.16	70	2000	1,573	1,032	685
	140				
	300				
	500	1000			
6.6 11 13.8	70		Consult Factory		
	140	Consu			
	300	Consu			
	500				

How To Order

Example:









