



## TSR-2

TSR-2, Adding Transformer

Code: M70701.

> Measuring Channels: 2 > Class 0,5 Power (VA): 15 > Class 1 Power (VA): 30 > Input current: 5 A

> Transformer type: Adding Transformer

#### Description

- O Accuracy class 0.5
- o Power 15 V-A
- The transformers added must have the same ratio
- O No input must be without a connection

## **Application**

Used to add the current to various AC electrical lines to obtain a common output current that is proportional to the sum of all currents. The current of various lines can be measured in a single unit.







# TSR-2

Current adding transformer

Current adding transformers fixed on a DIN rail

Code: M70701.

## **Specifications**

Mechanical characteristics					
Size (mm) width x height x depth	110 x 72.5 x 110 (mm)				
Weight (kg)	0,793				

# **TSR**Current adding transformer

CODE	TYPE	Measurement Range (A)	Class 0,5 Power (VA)	Class 1 Power (VA)	Class 3 Power (VA)
M70701.	TSR-2	5 A	15	30	-
M70702.	TSR-3	5 A	15	30	-
M70703.	TSR-4	5 A	15	30	-
M70704.	TSR-5	5 A	15	30	-

Current adding transformers must have the same primary ratio For other ratios, please ask









## TSR-2

Current adding transformers fixed on a DIN rail


Code: M70701.

#### Dimensions





#### Connections



MODELO	ENTRADAS	POTENCIA	CODIGO
TSR-2	2	15VA. CI 0,5	M70701
TSR-3	3	15VA. CI 0,5	M70702
TSR-4	4	15VA. CI 0,5	M70703
TSR-5	5	15VA. CI 0,5	M70704

**TSR** 

